## ZI-STE11000 // generator

## highlights

- very convenient for building sites as well as garden, leisure and camping activities
- electric start with battery and remote control
- 100% copper winding, synchronous generator,
- operating hours counter, AVR regulation
- low oil protection, gasoline fuel gauge (4,6 L at 75% straint), voltmeter
- chassis :4 wheels



## ZI-STE11000 // generator



## technical details

motor power s1 in W	13400
fuel capacity in I	30
starter	E-Start
speed in min-1	3600
sockets	1x 400V 3x230V; 1x230V(32A)
generator performance in W	11000
•	11000
sound power level in dB(A)	98
·	
sound power level in dB(A)	98

engine type	4-Takt OHV Loncin 2V78
fuel type	ROZ95
displacement in ccm	678
max. performance in W	12000
direct current	12V 8,3A
work duration in h	12
sound pressure level in dB(A)	89
net weight in kg	185
packaging length in mm	1.040
EAN code	9120039231532